SILVERGEAR

Wireless Ergonomic Mouse
Manual / Handleiding

NL

Koppelen met USB-ontvanger
Haal de USB-ontvanger uit de onderkant van de muis. Steek de USB-ontvanger in de USB-poort van uw PC. Zet de schakelaar op de muis op "ON". De muis en USB-ontvanger maken automatisch verbinding.

Slaap- en ontwaakfunctie
De muis gaat in slaapstand wanneer de muis een tijdje niet wordt gebruikt. Klik op een willekeurige knop op de muis om uit de slaapstand te halen. De indicator op de muis knippert, de USB-ontvanger is ingeschakeld.

Muis uitschakelen
Wanneer de muis niet in gebruik is, schakel uit naar "OFF". U kunt de USB-ontvanger in de PC laten of terugplaatsen aan de onderkant van de muis.

Herlaadbare batterijen
De muis kan gebruikt worden tijdens het opladen, alleen verlengt dit de laadtijd. De muis gaat automatisch uit bij een opgeladen batterij om overlading te voorkomen. Laadindicator: indicator brandt rood wanneer de muis oplaadt en schakelt uit wanneer de muis is opgeladen. Er is een zwakke verbinding als de indicator knippert. Check de verbinding. Het volledig opladen van de muis duurt 3 tot 4 uur en gaat 30 tot 60 dagen mee.

Inhoud technische parameters
Specificaties
Afmetingen: 105 x 73 x 60mm
Gewicht: 80,5 gram
Bereik: > 10m
Zendvermogen: +5db max
Voltage: 3,7v
Verrichtingsstroom: <10mA
Laadstroom: <300mA
Slaapstroom: <1 uA
Gevoeligheid: 3dpi modi: DPI 800-1200-1600 (aanpasbaar)

Computer systeemvereisten
Windows 2000
Windows XP
Windows Vista, Windows CE, Windows 7, Windows 10
Linux Android

Onderhoud
Probeer geen onderdelen van de muis te verwijderen of de lithium batterij te vervangen. Dit gaat ten koste van de garantie en kan voor kortsluiting zorgen wat kan resulteren in brand of een explosie.

De batterij kan voor ontlading zorgen als deze een tijdje niet gebruikt wordt. Gebruik de bijgeleverde oplader. Ontkoppel de muis wanneer de batterij volledig is opgeladen. Overladen gaat ten koste van de levensduur van de batterij.

Gebruik voor het schoonmaken van de muis een vochtige doek met een milde zeep. Oplosmiddelen en andere schoonmaakmiddelen kunnen schade aan de muis veroorzaken.

Stel de muis niet bloot aan een extreem hete of koude omgeving. Extreme temperaturen kunnen invloed hebben op de levensduur van de muis.

Probleemoplossingen
Hieronder volgen probleemoplossende scenario's voor de muis. Neem contact op met onze klantenservice als u een probleem met de muis niet kunt oplossen.

Storing	Mogelijke reden	Oplossing
De muis reageert niet	1. Een lege batterij 2. Powerschakelaar staat uit 3. De muis installeert het programma	1. Oplossing A: laad ten minste 15 minuten op Oplossing B: laad volledig op voor het eerste gebruik 2. Controleer of de schakelaar op "ON" staat 3. Controleer of de indicator aan de onderkant brandt
Niet mogelijk om USB te koppelen met ontvanger	1. De ontvanger is niet goed geplaatst 2. Lege batterij – schakelt automatisch uit	1. Verwijder de ontvanger en plaats opnieuw 2. Gebruik de muis wanneer hij volledig is opgeladen
De muisaanwijzer is onregelmatig of reageert langzaam	1. De muis is buiten het bereik van de ontvanger 2. Lage spanning 3. Vuil op de lazer aan de onderkant 4. De dpi van de muis is te laag	1. Plaats de muis dichter bij de ontvanger 2. Laad de muis op of vervang de batterijen 3. Gebruik een vochtige doek om de laser schoon te maken 4. Verander de dpi door de linkertoets en het middelste wiel tegelijk in te drukken
De muis laadt niet op	1. Lege batterij 2. Zwakke verbinding 3. Laadkabel is beschadigd	1. Neem contact op met de klantenservice 2. Controleer of de muis is verbonden met de oplader 3. Vervang de laadkabel

Oplaadbare batterij versie



Ergonomische muis
Deze muis heeft vitale en innovatieve eigenschappen met gezonde voordelen. Door de positie van uw pols en arm te veranderen, vermindert u pijn en ongemak. Te gebruiken op kantoor of tijdens het gamen.

EN

Connecting USB Receiver
Take out the receiver from the slot located at the bottom of the mouse and insert USB receiver into the USB port on your computer.
For the first time use, please toggle the power switch (on the bottom of the mouse) to the "ON" position, the mouse and USB receiver will automatically connect.

Intelligent sleep and wake up
The mouse has automatic wake up and sleep function. If it not use for a while, the mouse will automatically enter a dormant status, you can press any button on the mouse to wake up the mouse. The mouse lights will continue to flash and keep working with the receiver.

Turning off the mouse
When the mouse does not need to be used, toggle the power switch to the "OFF" position. You can leave the USB receiver in computer or put it back into the slot under the mouse for safe keeping.

Rechargeable batteries (using 5 c)
It uses 5C rechargeable lithium battery. Please use the original charging line(provided by original factory). The product can be used while charging, but will extend the charging time. When battery is low, it will power off automatically to avoid the danger of excessive discharge. Charge indicator: light bright for charging status, lamp light will stay on. If it is flashing, there may be poor contact, please check the connection. It need 3–4 hours for a full charge and will last 30 to 60 days. It can be recharged 300 times.When charging, charging port LED shine red; Full charge, LED turn off.

Appendix
Technical parameters
Specification
Measurements (LWH):105 x 73 x 60(mm)
Weight (grams): 80.5g
Operational range: > 10m
Transmit power: +5db max
Operation voltage: 3,7v
Operation current: < 10mA
Charging current: <300mA
Sleep current: < 1 uA
Sensitivity: 3 dpi modes: DPI 800–1200–1600 Adjustable

Computer system requirements:
Windows 2000
Windows XP
Windows Vista, Windows CE, Windows 7, Windows10
Linux Android

Maintenance
Do not attempt to remove the device or replace lithium battery , or it will make the warranty be invalid and may cause it to short circuit; fire and explosion danger.
The battery will discharge if do not use for a long time.
Use the specified charger. Disconnect the device after the battery has been fully charged. Overcharging the battery will shorten the life of the battery.
Use only a damp cloth with mild soap to clean the device. Solvents and other cleaning agents may cause damage to the device.
Don't expose device to very hot or very cold environment. Extreme temperature can make electricity shorten the mouse life.

Troubleshooting
Following are some basic troubleshooting scenarios for the device. Please contact Silvergear if you're unable to resolve any issues with the device.

Malfunction	The possible reasons	The solution
The mouse does not respond	1 , The battery is low 2, Power switch is turned off 3, The device is installing the driver	1,Solution A: charge for at least 15 minutes Solution B: if using for the first time propose a full charge before use 2,Check if the switch has been turn to "ON" position 3, Check the light on the buttom of mouse if is bright
unable to conn–ect to the USB receiver	1,The receiver not inserted correctly 2,Low battery shut–down automatically	1,Pull out the receiver and re–insert into USB port 2,Use the mouse on a full charge again
the mouse poin–ter is irregular or slow to respond	1,Equipment may not be the optimal receiving range 2,Low voltage 3,Dust and oil on the laser at the bottom 4,The mouse DPI is too low	1,Move mouse closer to the receiver 2,Please charge or change batteries 3,Use wet cloth clean the bottom of the laser 4,change the DPI by press left key and middle wheel together
Product can not charge	1,Low battery 2,Poor connection 3,Charging line damaged	1,Please contact the local dealer to replace 2,Check whether the product is connected to the charger safely. 3,Replace the new charging line

Rechargeable battery version



This mouse is full of vitality, innovation, and has many healthy benefits. By changing the way you use your wrist and arms, you will effectively reduce pain and discomfort. Add rubber oil coating to prevent sweaty fingers from sliding. From the office to gaming, using the optical vertical mouse is comfortable and healthy.

www.silvergear.eu

KARSTEN INTERNATIONAL
Overschiestraat 63
1062 XD Amsterdam
The Netherlands
info@silvergear.eu

art. no.: 1079/ batch no.: 20314